

# Square Electrical Box Adapter Plate

Electrical Adapter Compatible with Arecont Vision Costar Cameras and Common Electrical Boxes

## AV-EBAS

Square Electrical Box Adapter Plate

### Features:

- Easy Installation and Superior Design
- Heavy Duty Enclosure Protection for Applications in Harsh Environments
- Die-Cast Aluminum is Resistant to Impact and Salt Damage

### Compatibility\*

Compatible with 3/4" NPT standard

Works with MegaView® Series, MicroBullet®, SurroundVideo®, SurroundVideo G5, AV-JBA, AV-WMJB, AV-SWMJB, MCD-WMT, MDD-WMT, HSG2-WMT, and AV-PMJB

### Mechanical

<b>Casing</b>	Die-cast aluminum
	IP66 weather proof standard
	IK-10 impact-resistant
<b>Color</b>	Ivory (Pantone Cool Gray 1C)
<b>Dimensions</b>	4.7" L (120mm) x 0.15" W (4mm) x 4.7" H (120mm)
<b>Weight</b>	<b>w/o Camera</b> 0.33lbs (0.13kg)

Hole No.	Model Compatibility	Thread Size
1	AV-JBA, AV-WMJB, AV-PMJB, MegaView 2 (standard), SurroundVideo, SurroundVideo G5	8-32
2	HSG2-WMT, AV-WMJB bracket, AV-PMJB bracket, MegaView 2 bracket	8-32
3	AV-SWMJB, MCD-WMT, MDD-WMT	8-32
4	MicroBullet	8-32
5	Single gang box	-
6	Double gang box	-
7	4S box (4" square, 4" octagonal)	-
8	4-11/16" square box	-

### Quick Installation:

1. Pass cables through the center hole of the adapter plate.
2. Attach the adapter plate to the electrical box (sold separately) using the appropriate hardware and mounting holes.
3. Attach the compatible part noted above.

\* The mounting plate on all MegaDome® Series cameras, SurroundVideo G5 Mini, SurroundVideo Omni G3, MicroDome® Duo, and the D4SO-3 housing negate the need for a separate electrical box adapter plate and therefore this accessory is not applicable.

