

# Round Electrical Box Adapter Plate

Electrical Adapter Compatible with Arecont Vision Costar Cameras and Common Electrical Boxes

## AV-EBAR

Round Electrical Box Adapter Plate

### Features:

- Easy Installation and Superior Design
- Heavy Duty Enclosure Protection for Applications in Harsh Environments
- Die-Cast Aluminum is Resistant to Impact and Salt Damage

### Compatibility\*

Compatible with 3/4" NPT standard

Works with MegaBall® Series, MicroDome® -S cameras, SurroundVideo®, SurroundVideo G5, SurroundVideo Omni Series\*, MCD-CMT, and MB2-JBA

### Mechanical

<b>Casing</b>	Die-cast aluminum
	IP66 weather proof standard
	IK-10 impact-resistant
<b>Color</b>	Ivory (Pantone Cool Gray 1C)
<b>Dimensions</b>	Ø6" (152.4mm) x 0.15" W (4mm)
<b>Weight</b>	<b>w/o Camera</b> 0.4lbs (0.18kg)

Hole No.	Model Compatibility	Thread Size
1	MegaBall Series wall mount (legacy), MCD-CMT	8-32
2	MegaBall Series dome mount	M3 x 0.5
3	MegaBall Series bell mount, MicroDome Series surface mount	8-32
4	SurroundVideo, SurroundVideo G5, and, MB2-JBA	8-32
5	4S box	-
6	4-11/16" square box	-
7	Single gang box	-
8	Double gang box	-
9	SurroundVideo Omni Series*	8-32

### Quick Installation:

1. Pass cables through the center hole of the adapter plate.
2. Attach the adapter plate to the electrical box (sold separately) using the appropriate hardware and mounting holes.
3. Attach the compatible part noted above.

\* The mounting plate on all MegaDome® Series cameras, SurroundVideo G5 Mini, SurroundVideo Omni G3, MicroDome Duo, and the D4SO-3 housing negate the need for a separate electrical box adapter plate and therefore this accessory is not applicable.

